

PASHA MAC10



GENERAL FEATURES

- The capacity of music and announcement with 10 zones
- Raising multiples of 10
- Zone selection indicators
- Indicators and buttons that enables the music broadcast
- Connection with PMIC-10, remote controlling with D-Sub connector
- 3 different production types, best for your system characteristics
- The special type of input and output connectors



PASHA MAC10 music and announcement control module controls the zones that the music and announcement will be made. It is used in all applications which zone number is over 3. As a general description, it conveys the music and announcement information. In case of that the system is over 10 zones, it must be used extra one. For each 10 zones, it must be added one more extra.

PASHA MAC10 announcement control module is produced in 3 different types. In first two of these types, it is used an amplifier, which has enough energy, in each output zone if the power of speakers in zones is high. If only one amplifier isn't enough, it can be added extras. The other application is that it is worked with an amplifier by the combination of the power of speakers. In this application, all the music broadcasts are stopped while making an announcement. When the announcement is completed, the music broadcast activates automatically. It is connected 6 amplifiers to this type of PASHA MAC10 announcement control module in maximum. In the other application, there is no limit.

TECHNICAL SPECIFICATIONS

Supply Voltage	220Vac ±%5
Supply Frequency	50 Hz, ±%2
Power Consumption	80W
Inputs and Outputs	10 Adet, Nomina - 1,5 Vrms / 100Vrms
Frequency Reply	20Hz-20kHz
Relative Humidity	%80
Operating Temperature	-10°C ~ 50°C
Storage Temperature	-30°C ~ 70°C
Dimensions	482 x 86 x 120mm & 482 x 86 x 240mm
Weight	4,00 Kg